

**This Page Is Inserted by IFW Operations  
and is not a part of the Official Record**

## **BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

## **IMAGES ARE BEST AVAILABLE COPY.**

As rescanning documents *will not* correct images,  
Please do not report the images to the  
Image Problem Mailbox.

**THIS PAGE BLANK (USPIC)**




PCT

WORLD INTELLECTUAL PROPERTY ORGANIZATION  
International Bureau

INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification <sup>6</sup> : <b>H04B 1/10</b>		A2	(11) International Publication Number: <b>WO 99/16179</b>
			(43) International Publication Date: 1 April 1999 (01.04.99)
(21) International Application Number: PCT/IB98/01271		(81) Designated States: CN, JP, KR, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(22) International Filing Date: 19 August 1998 (19.08.98)			
(30) Priority Data: 9720285.7 25 September 1997 (25.09.97) GB 9725492.4 3 December 1997 (03.12.97) GB		Published Without international search report and to be republished upon receipt of that report.	
(71) Applicant: KONINKLIJKE PHILIPS ELECTRONICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).			
(71) Applicant (for SE only): PHILIPS AB [SE/SE]; Kottbygatan 7, Kista, S-164 85 Stockholm (SE).			
(72) Inventors: MOORE, Paul, Anthony; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL). DAVIE, Alan, James; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).			
(74) Agent: MOODY, Colin, J.; Internationaal Octroobureau B.V., P.O. Box 220, NL-5600 AE Eindhoven (NL).			

(54) Title: IMPROVEMENTS IN OR RELATING TO PHASING RECEIVERS



(57) Abstract

A phasing receiver comprises mixing means (16, 18, 20, 22) for frequency converting an input signal to quadrature related low IF signals (I, Q). The low IF signals are applied to a polyphase filter (24) which functions as a low pass and an adjacent channel rejection filter. Means (Figures 3 to 5 - not shown) for fine adjustment of the phase and/or amplitude of the input signals are provided for improving the image rejection due to mismatches in an input stage of the polyphase filter (24).

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LJ	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

## DESCRIPTION

## IMPROVEMENTS IN OR RELATING TO PHASING RECEIVERS

## 5 Technical Field

The present invention relates to phasing receivers and particularly, but not exclusively to polyphase or sequence - asymmetric receivers which may be implemented as an integrated circuit.

## 10 Background Art

A popular type of architecture for use as an integrated receiver is a zero - IF architecture in which an input signal is frequency downconverted to a zero - IF using quadrature mixers, the wanted signals are selected from the products of mixing using low pass filters and the wanted signals are processed further to provide a demodulated output.

Most of the limitations which beset the zero - IF receiver arise either directly or indirectly from the fact that components of wanted signals translated down to IF frequencies at or around DC cannot be distinguished from components of unwanted signals which appear in the same frequency range as a result of inherent circuit deficiencies.

The above - mentioned limitations in a zero - IF receiver may be eliminated substantially in a low - IF superheterodyne receiver but this would suffer from an image response that could not be eliminated by realistic front-end filters.

Another receiver architecture termed a phasing receiver, is a low - IF receiver based on the principle of the image - reject mixer in which the image response is removed by cancellation, rather than filtering, but the level of image rejection which can be achieved, even in fully - integrated form, is severely limited by the degree of matching which can be obtained between nominally identical components. A particular example of a phasing receiver is the polyphase or sequence - asymmetric receiver in which the conventional IF

filters, IF phase shifters and IF signal combiner are replaced by a single polyphase IF filter. This very substantially increases the level of image rejection which can be obtained. In spite of the increased level of image rejection there may still a need to improve further the level of image rejection.

5

#### Disclosure of Invention

An object of the present invention is to improve the image rejection capability of a phasing receiver.

According to one aspect of the present invention there is provided a  
10 phasing receiver having a polyphase or sequence - asymmetric gyrator filter in which lack of image rejection is improved by the fine adjustment of the phase and/or amplitude of input signals.

According to a second aspect of the present invention there is provided a phasing receiver comprising an input, first and second signal mixing means  
15 for providing quadrature related low IF frequencies, a polyphase filter having inputs coupled to outputs of the first and second signal mixing means and signal demodulating means coupled to outputs of the polyphase filter, and means for effecting fine adjustment of the phase and/or amplitude of signals applied to the inputs of the polyphase filter to compensate for less than  
20 optimum image rejection.

By means of the present invention fine adjustment of the amplitude and/or phase of the pair of IF signals feeding a polyphase IF filter can further improve the level of image rejection which can be obtained, typically by at least 10dB.

25

#### Brief Description of Drawings

The present invention will now be described, by way of example, with reference to the accompanying drawings, wherein:

Figure 1 is a block schematic diagram of a polyphase receiver,

30 Figure 2 is a simplified circuit diagram of a current - fed polyphase or sequence - asymmetric gyrator filter,

Figures 3A and 3B show one arrangement by which amplitude may be adjusted,

Figures 4A and 4B show another arrangement by which amplitude may be adjusted,

5 Figure 5 shows one arrangement by which phase may be adjusted, and

Figures 6 to 13 are graphs showing the lack of image rejection due to errors in the resistance R3, the capacitance C6 and the cross coupling gyrator JC17, shown in Figure 2.

10 In the drawings the same reference numerals have been used to indicate corresponding features.

#### Modes for Carrying Out the Invention

Referring to Figure 1, the illustrated polyphase receiver comprises a low IF receiver in which the local oscillator frequency is offset by, for example, half  
15 the channel bandwidth from the nominal carrier frequency of an input signal received by an antenna 10.

Ignoring the components in the box 100, the antenna 10 is coupled by an RF amplifier 12 to a signal splitter junction 14. First and second mixers 16, 18 each have a first input coupled to the junction 14. A local oscillator 20 is  
20 coupled to the second input of the first mixer 16 and, by way of a 90 degree phase shifter 22, to a second input of the second mixer 18. The in-phase products I of mixing present at an output of the first mixer 16 are applied to a first input 26 of a current-fed polyphase filter 24. The quadrature phase products Q of mixing present at an output of the second mixer are applied to  
25 a second input 28 of the filter 24.

The polyphase filter 24 functions as an image rejection filter and a channel selectivity filter. Outputs 30, 32 of the filter 24 are coupled to a demodulator 34 having an output terminal 36.

Referring to the components in the box 100, the signal from the RF  
30 amplifier 12 is applied to a superhet frequency down conversion stage comprising a mixer 102 to which an output from a local oscillator 104 is

applied. A bandpass filter 106 selects an IF signal which is amplified in an IF amplifier 108 and supplied to the junction 14. Thus the quadrature frequency down conversion stage operates on the IF signal instead of the RF signal which will be the case if the superhet stage is not present. For convenience of description it will be assumed that the superhet stage is not present.

Although the polyphase filter 24 has been identified as being current fed, it may be voltage fed depending on the application.

Figure 2 illustrates an embodiment of a 5th order polyphase filter 24. The filter comprises 2 sets of stages, corresponding stages in each set being identical. For convenience of description only one set of the stages will be described and the corresponding components in the non-described set will be shown in parenthesis. A first stage of the filter comprises a source resistor R1 (R3), a capacitor C1 (C6) and a transconductor JC1 (JC9) are coupled in parallel between signal rails 38, 40. A cross-coupled gyrator consisting transconductors JC26 and JC17 is coupled to the signal rails 38, 40. A current source J1 (J2) representing the inputs is coupled to the signal rails 38, 40. The current sources J1, J2 correspond to inputs 26, 28, respectively, in Figure 1.

The second, third and fourth stages are of identical layout and will be described collectively. A transconductor JC2 (JC10), JC4 (JC12), JC6 (JC14) is connected in parallel with a capacitance C2 (C7), C3 (C8), C4 (C9) and another transconductor JC3 (JC11), JC5 (JC13), JC7 (JC15) between signal rails 42, 44. Cross coupled gyrators JC19 (JC18), JC21 (JC20) and JC23 (JC22) are coupled to the signal rails 42, 44 of the respective stages. The fifth stage of the filter comprises a transconductor JC8 (JC16), capacitance C5 (C10) and resistor R2 (R4) connected in parallel between signal lines 46, 48. A cross coupled gyrator JC25 (JC24) is coupled to the signal rails 46, 48. Outputs 30, 32 are derived from the fifth stages.

The response of the polyphase filter 24 is centred on the low IF frequency, for example 12.5kHz in the case of 25kHz channel spacing. The component values can be determined by a number of known techniques and reference may be made to "Handbook of Filter Synthesis" by Anatol I. Zverev,



published by John Wiley and Sons Inc., June 1967. Once the values of the resistors R2, R2, R3 and R4 and the transconductances of the transconductors JC1 to JC16 have been set the capacitances C1 to C5 (C6 to C10) determine the shape of the filter response and the filter bandwidth. The centre frequency of the filter, in this example 12.5kHz, is determined by the cross-coupling gyrators JC17 to JC26 as discussed by J.O. Voorman, "The Gyrator as a Monolithic Circuit in Electronic Systems" PhD Thesis of Catholic University of Nijmegen, The Netherlands, 16 June 1977, pages 91 to 103.

A polyphase filter is normally fabricated as an integrated circuit and if the components were truly identical, the response would be a perfect as can be designed. However due to limited matching capabilities of the components, image rejection by the polyphase filter will be less than perfect.

The present invention endeavours to reduce, if not remove, the mismatches in component values by predistorting the amplitude and/or phase of drive signals in order to correct for the frequency dependent errors produced by the mismatches.

An examination of the effects of these mismatches has shown that mismatches between components in the early stages, especially the first stage, are responsible for the degrading of the image rejection. However because these components are in the early stages, the errors which they produce do not vary rapidly across the bandwidth of the filter. It has been found that it is possible to substantially correct for these errors by means of an essentially constant phase and/or amplitude correction inserted in the RF signal path, the local oscillator signal path or the low IF path. If the superhet stage is present, the correction would be in the higher IF path, the local oscillator signal path or the low IF path.

Referring to Figure 2, the mismatches are considered are those between (a) the source resistors R1 and R3, (b) the first capacitors C1 and C6, (c) the amplitude match of the forward and reverse paths of the first cross-coupling gyrator JC17, and (d) the phase match of the forward and reverse paths of the first cross-coupling gyrator JC17. Mismatch due to (a) above can be reduced

by fine adjustment of the phase of the IF input signals. The mismatch due to (b) above can be reduced by fine adjustment of the amplitude of the IF signals. The mismatch due to (c) above can be reduced by fine adjustment of the amplitude of the IF input signals and lastly the mismatch due to (d) above can be reduced by fine adjustment of the phase of the IF input signals.

Referring to Figure 1, the adjustment of the amplitude and/or phase of the IF input signals can be effected in the RF signal path to the first and second mixers 16, 18, for example at the junction 14. Also phase adjustment can be effected in the output path of the local oscillator 20 but it is not considered viable to make amplitude adjustments because the mixers 16, 18 are normally intentionally overdriven by the local oscillator 20. Amplitude adjustments may also be effected in the low IF signal paths between the outputs of the mixers 16, 18 and the filter inputs 26, 28, respectively. Although phase adjustments are theoretically possible in these latter signal paths, in reality they are impractical.

Figures 3A and 3B illustrate a method of effecting an amplitude adjustment in an analogue manner. Figure 3A shows a fixed potentiometer comprising resistors R1, R2 connected in series across an input of one of the signal paths and a junction 50 of these resistors being connected to an output. Figure 3B shows a variable potentiometer comprising a resistive potentiometer VR1 connected in series with a fixed resistor R3. An output is taken from the wiper of the potentiometer VR1. The values of the potentiometer VR1 and the resistor R3 can be determined statistically to introduce a sufficient adjustment range. The values of the resistors R1, R2 are then chosen to achieve the same attenuation as VR1 and R3, when the potentiometer VR1 is in its mid position. The potentiometer VR1 permits adjustments of the amplitude error to be made in each individual receiver to maximise image rejection.

The amplitude adjustment arrangement shown in Figures 4A and 4B differs from that shown in Figures 3A and 3B by a digitally controlled potentiometer VR2 being used in place of the combination of the potentiometer VR1 and the fixed resistor R3. The digital value is determined by measuring

image rejection and adjusting the attenuation to maximise the image rejection.

Figure 5 illustrates an arrangement for adjusting phase. In one of the signal paths an adjustable nominal 45 degree phase lead network PA1 is provided and in the other of the signal paths an adjustable nominal 45 degree phase lag circuit PA2 is provided. The circuits PA1 and PA2 each comprise a varactor diode VAD and a fixed resistor R4. Phase adjustment is effected by altering the capacitance value of the respective varactor diodes VAD. This can be effected digitally in which a stored digital value is applied to a digital to analogue converter DAC which supplies an analogue signal to a controller 52. The controller 52 produces control voltages  $VC_i$  and  $VC_o$  to adjust the varicap values electronically in the same direction. Although Figure 5 indicates a nominal relative phase difference of 90 degrees, this can be varied to give a smaller or greater phase difference depending on the respective phase mismatch in the receiver.

In practice it has been found that mismatches between capacitances C1 and C6 are corrected by adjustments in amplitude whereas mismatches between source resistors are corrected by phase adjustments. In other words the amplitude and phase adjustments act in an essentially orthogonal manner which enables each adjustment to be carried out substantially independently of the other.

Figures 6 to 13 are graphs which illustrate the effects of mismatches and the improvements obtainable by making the adjustments discussed. All the graphs are plots of frequency in Hz against the output across the resistor R2 in dBA. They all show a frequency shift of 300kHz and a -3dB bandwidth of 80kHz.

In Figures 6 to 13, the graphs have been folded about zero frequency and comprise a positive frequency part P and a negative frequency part N. Any imperfection is shown on the negative frequency part of the characteristic.

Taking Figure 6 as an example the effects of the mismatch in the resistance R3 are shown as a peak of increasing amplitude as the value of the resistance R3 is increased in 5% increments up to a maximum of 25%.

In Figure 7, the full line shows the peak due to a 5% error in the resistance R3 and in broken lines the effect of improvement obtained by the fine adjustment of the input phase. The dip in the broken line is due to the fact the errors are frequency dependent.

5        Figure 8 is a graph illustrating a lack of image rejection caused by increasing the value of the capacitance C6 shown in Figure 2 by 25% in steps of 5%.

Figure 9 is a graph illustrating by a full line a lack of image rejection caused by 5% error in capacitance C6 shown in Figure 2 improved by fine  
10        adjustment of the input amplitude (broken lines).

Figure 10 is a graph illustrating the lack of image rejection caused by increasing the value of amplitude of a cross-coupling gyrator JC17 shown in Figure 2 by 25% in steps of 5%.

Figure 11 is a graph illustrating by a full line the lack of image rejection  
15        caused by 5% error in amplitude of the cross-coupling gyrator JC17 shown in Figure 2 improved by fine adjustment of input amplitude (broken lines).

Figure 12 is a graph illustrating the lack of image rejection caused by a phase lead/lag of 5 degrees of the cross-coupling gyrator JC17 shown in Figure  
2.

20        Finally, Figure 13 is a graph illustrating by a full line the lack of image rejection caused by a 5 degree error in phase of the cross-coupling gyrator JC17 shown in Figure 2 improved by fine adjustment of input phase (broken lines).

These mismatches are, in general, the most significant ones in terms of  
25        the resultant lack of image rejection although the actual degree of mismatch used in these examples is much greater than would normally be expected in practice. They have been used solely to make the resultant lack of image rejection clear.

From reading the present disclosure, other modifications will be apparent  
30        to persons skilled in the art. Such modifications may involve other features which are already known in the design, manufacture and use of phasing

receivers and component parts thereof and which may be used instead of or in addition to features already described herein.

#### Industrial Applicability

- 5           Phasing receivers, fabricated as integrated circuits, for use in telecommunications products.

## CLAIMS

1. A phasing receiver having a polyphase filter in which lack of image rejection is improved by the fine adjustment of the phase and/or amplitude of input signals.
2. A phasing receiver comprising an input, first and second signal mixing means for providing quadrature related low IF frequencies, a polyphase filter having inputs coupled to outputs of the first and second signal mixing means and signal demodulating means coupled to outputs of the polyphase filter, and means for effecting fine adjustment of the phase and/or amplitude of signals applied to the inputs of the polyphase filter to compensate for less than optimum image rejection.
3. A phasing receiver as claimed in Claim 2, characterised in that the adjustment means is provided to adjust phase and/or amplitude of the input signals to at least one of the first and second signal mixing means.
4. A phasing receiver as claimed in Claim 2, characterised in that local oscillator signal generating means is coupled to the first and second signal mixing means, and in that the adjustment means comprise phase adjustment means provided in the local oscillator signal path.
5. A phasing receiver as claimed in Claim 2, characterised in that local oscillator signal generating means is coupled to the first and second signal mixing means, and in that the adjustment means comprise amplitude adjustment means provided in the local oscillator signal path.
6. A phasing receiver as claimed in Claim 2, characterised in that the adjustment means comprise amplitude adjustment means provided in a signal path to at least one input of the polyphase filter.

7. A phasing receiver as claimed in Claim 2, characterised in that the adjustment means comprise phase adjustment means provided in a signal path to at least one input of the polyphase filter.

5

8. A phasing receiver as claimed in any one of Claims 2 to 7, characterised in that the polyphase filter has N-stages, where N is an integer, and in that the phase adjustment means are provided to compensate for mismatches in an input stage.

10

9. A phasing receiver as claimed in any one of Claims 1 to 8, fabricated as an integrated circuit.

1/8




FIG. 1



2/8




FIG. 2

3/8




FIG. 3A




FIG. 3B




FIG. 4A




FIG. 4B

4/8




FIG. 5

5/8




FIG. 6




FIG. 7

6/8




FIG. 8




FIG. 9

7/8




FIG. 10




FIG. 11

8/8




FIG. 12




FIG. 13

**This Page Blank (uspto)**





## INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification<sup>6</sup> :**H04B 1/10, H04B 1/26, H03H 17/02****A3**

(11) International Publication Number:

**WO 99/16179**

(43) International Publication Date:

1 April 1999 (01.04.99)

(21) International Application Number: PCT/IB98/01271

(22) International Filing Date: 19 August 1998 (19.08.98)

(30) Priority Data:

9720285.7	25 September 1997 (25.09.97)	GB
9725492.4	3 December 1997 (03.12.97)	GB

(71) Applicant: KONINKLIJKE PHILIPS ELECTRONICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).

(71) Applicant (for SE only): PHILIPS AB [SE/SE]; Kottbygatan 7, Kista, S-164 85 Stockholm (SE).

(72) Inventors: MOORE, Paul, Anthony; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL). DAVIE, Alan, James; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).

(74) Agent: MOODY, Colin, J.; Internationaal Octrooibureau B.V., P.O. Box 220, NL-5600 AE Eindhoven (NL).


(81) Designated States: CN, JP, KR, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).

**Published***With international search report.**Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.*

(88) Date of publication of the international search report:

10 June 1999 (10.06.99)

(54) Title: IMPROVEMENTS IN OR RELATING TO PHASING RECEIVERS



## (57) Abstract

A phasing receiver comprises mixing means (16, 18, 20, 22) for frequency converting an input signal to quadrature related low IF signals (I, Q). The low IF signals are applied to a polyphase filter (24) which functions as a low pass and an adjacent channel rejection filter. Means (Figures 3 to 5 – not shown) for fine adjustment of the phase and/or amplitude of the input signals are provided for improving the image rejection due to mismatches in an input stage of the polyphase filter (24).

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

# INTERNATIONAL SEARCH REPORT

International application No.

PCT/IB 98/01271

## A. CLASSIFICATION OF SUBJECT MATTER

**IPC6: H04B 1/10, H04B 1/26, H03H 17/02**  
According to International Patent Classification (IPC) or to both national classification and IPC

## B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

**IPC6: H04B, H03H**

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

**SE,DK,FI,NO classes as above**

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

## C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 0576082 A1 (PHILIPS ELECTRONICS N.V.), 29 December 1993 (29.12.93), abstract  --	1-9
A	US 4723318 A (CHRISTOPHER B. MARSHALL), 2 February 1988 (02.02.88), abstract  --	1-9
A	EP 0344852 A1 (N.V. PHILIPS' GLOEILAMPENFABRIEKEN), 6 December 1989 (06.12.89), abstract  -- -----	1-9

☐ Further documents are listed in the continuation of Box C.

☒ See patent family annex.

\* Special categories of cited documents:

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

"I" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

**7 April 1999**

Date of mailing of the international search report

**13 -04- 1999**

Name and mailing address of the ISA/  
Swedish Patent Office  
Box 5055, S-102 42 STOCKHOLM  
Facsimile No. +46 8 666 02 86

Authorized officer

**Bengt Romedahl**  
Telephone No. +46 8 782 25 00

**INTERNATIONAL SEARCH REPORT**

Information on patent family members

02/03/99

International application No.

PCT/IB 98/01271

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 0576082 A1	29/12/93	JP 6077853 A	18/03/94
		SG 49297 A	18/05/98
		US 5715529 A	03/02/98
-----			
US 4723318 A	02/02/88	DE 3585366 A	19/03/92
		EP 0185417 A,B	25/06/86
		SE 0185417 T3	
		GB 2168868 A	25/06/86
		JP 7075329 B	09/08/95
		JP 61148923 A	07/07/86
-----			
EP 0344852 A1	06/12/89	SE 0344852 T3	
		DE 68908019 T	17/03/94
		ES 2044056 T	01/01/94
		JP 2026406 A	29/01/90
		KR 9708794 B	29/05/97
		NL 8801412 A	02/01/90
		US 4914408 A	03/04/90
-----			